



Qoltec Overcurrent Circuit Breaker C32 | Fuse | AC | 32A | 3P

Product code: 52593

Qoltec brand overcurrent circuit breaker will effectively protect and safeguard the installation and the connected electrical loads from the effects of overload and short circuit. Mounting on DIN rail, TH35. Equipped with an electromagnetic and thermal trip.

PROTECT YOUR EQUIPMENT - USE RELIABLE OVERCURRENT CIRCUIT BREAKERS



Every circuit of an electrical installation must be adequately protected from the effects of **overloads and short circuits**, so it is **mandatory to use appropriate protection**. One such device is an **overcurrent circuit breaker**, this element **interrupts the continuity of the circuit when the current in the circuit is too high**. It effectively eliminates the risk of damage to the installation caused by a temporary overvoltage or short circuit, which can lead to the destruction of the network and connected equipment.

APPLICATION

Overcurrent circuit breakers are used in a wide variety of applications, including **domestic installations, workshops, production halls and many other places** where it is important to protect electrical equipment. **Our product is a full:**

- short-circuit protection,
- quality guarantee,
- easy rail mounting,
- equipped with an electromagnetic and thermal trip.

CONFIDENCE CONFIRMED BY A WARRANTY



Do you care about the high quality of the product you buy? Our solutions will meet your expectations. The product comes with a **24-month warranty valid from the date of purchase.**

TECHNICAL DATA

Producer	Qoltec
Rated current	32A
Characteristic category	C
Class	II
Electrical life	4000
Mechanical life	10000
Number of poles	3
Type of assembly	TH35
IP rating	IP20
Additional information	Equipped with an electromagnetic and thermal trip.
Material	PA66 + cooper
Dimensions (D/L x W x H)	75 x 53 x 86 mm
Net weight [kg]	0.260
Gross weight [kg]	0.261
Certificate	CE
Warranty	24 month
EAN code	5901878525938