



Qoltec Specialist charger for 12V LiFePO4 batteries | 10A | PF 0.9 | LED | Smart charging

Product code: 52670

The automatic 12.8V LiFePO4 battery charger is a practical solution for the daily charging of lithium iron phosphate batteries. The device operates in CC/CV mode, offering a charging current of 10A and an output voltage of 14.6V 0.2V. With a power output of 150W, efficiency of up to 90%, active fan cooling, an LED indicator and reverse polarity protection, it enhances both convenience and safety of use. It does not support lead-acid batteries.

AUTOMATIC LIFEPO4 CHARGING – CORRECT SETTINGS WITHOUT MANUAL ADJUSTMENT



High efficiency and effective cooling

With a power output of 150W and 90% efficiency, it ensures efficient battery charging whilst making effective use of energy. A built-in fan actively cools the components, allowing the charger to operate stably even during longer charging cycles. An LED allows you to quickly check the device's operating status without the need for additional measurements. A red LED indicates that the charger is charging the battery, whilst a green LED indicates that the charging process is complete.

SMART CC/CV CHARGING – TAILORED TO LiFePO4 BATTERIES



Two-stage CC/CV charging mode

The charger uses a two-stage CC/CV charging mode, suitable for 12.8V LiFePO4 batteries. In the first CC (Constant Current) phase, the device charges the battery with a constant current of up to 10A 0.2A, ensuring rapid recharging. Once the correct voltage level is reached, it switches to the CV (Constant Voltage) phase, during which it maintains the voltage at 14.6V 0.2V, whilst the charging current gradually decreases. This allows for a controlled completion of the charging process without the need for manual adjustment.

CONNECT CORRECTLY, CHARGE SAFELY



Connecting a LiFePO4 battery correctly – starting charging safely

Before starting to charge, ensure that the battery is a 12.8V LiFePO4 type and that the charger is disconnected from the mains. Connect the red terminal (+) to the positive terminal of the battery, then the black terminal (–) to the negative terminal. Once you have checked that the connections are correct, connect the charger to a 230V AC mains supply. The device will automatically start charging in CC/CV mode, which is tailored to the characteristics of LiFePO4 batteries. Once the process is complete, first disconnect the charger from the mains, then remove the black terminal, and finally the red one.

COMPREHENSIVE PROTECTION, AUTOMATIC MONITORING, SAFE CHARGING

Multi-level protection – safe charging at every stage

The charger is equipped with a range of safety features that protect both the device and the connected battery throughout the entire charging process. **Reverse polarity protection** safeguards against the effects of incorrect terminal connection, **overvoltage protection** limits the risk of exceeding the permissible voltage, and **thermal protection** responds to excessive temperature rises. Additional **short-circuit protection** enhances safety in the event of a short circuit. Once the appropriate charge level is reached, **the device automatically stops the charging process**, meaning it does not require constant supervision.

TRUST BACKED BY A GUARANTEE

This product comes with a 24-month warranty

Do you want to be sure of the high quality of the product you're buying? Our solutions will meet your expectations. The chargers we offer come with a **24-month warranty** valid from the date of purchase.

TECHNICAL DATA

Producer	Qoltec
Power	150W
Input voltage	220-240V
Output voltage	14.6V 0.2V
Battery voltage	12.8V
Type of charging	CC-CV
Output current	10A 0.2A
Connector	Red and black alligator clips
Efficiency	90%
Cooling system	1 x Fan
Display	No
Protection	reverse polarity protection overvoltage protection thermal protection short-circuit protection automatic charge termination
OTHER PARAMETERS	
EAN code	5901878526706